

Specifications

Model name	SQ47	SQ57
Effective length	90 to 3,740mm ^{(*)1}	70 to 3,770mm ^{(*)2}
Accuracy	±(1.5+1.5L/1000)μm	
Resolution	Selectable from 0.005/0.01/0.05/0.1/0.5/1μm	
Maximum response speed	200m/min	
Vibration resistance	250m/s ² (50 to 2,000Hz)	
Impact resistance	980m/s ² (11ms)	
Protective design grade	IP67	
Consumption current	1.35W typ (FANUC/Mitsubishi Electric/Yaskawa Electric) 2.1W typ (SIEMENS)	
Power supply voltage	DC5V (FANUC/Mitsubishi Electric/Yaskawa Electric) DC24V (SIEMENS)	
Operating temperature	0 to 50°C	
Output signal	Compatible with each serial interface	
Option	Connection cable CH23 Series (Mitsubishi Electric / Yaskawa Electric) CH23A Series (FANUC) CH22 Series (SIEMENS)	




Table1
<FANUC/Mitsubishi Electric>
(Mitsubishi Electric: Polarity + only)

Model name	Polarity	Resolution	Model name	Polarity	Resolution
S		0.005μm	T		0.005μm
A		0.01μm	F		0.01μm
B	+	0.05μm	G	-	0.05μm
C		0.1μm	H		0.1μm
D		0.5μm	J		0.5μm
E		1μm	K		1μm



<Yaskawa Electric/SIEMENS>

Model name	Polarity	Resolution
S		0.005μm
A	+	0.01μm

(*) Mitsubishi Electric: fix (center of effective length)
SIEMENS: fix

(*1) For effective length exceeding 3,740 mm, please contact our sales department.
(*2) For effective length exceeding 3,770 mm, please contact our sales department.

Dimensions



Please contact us for more details.

△ To use this product safely, please read the instruction manual carefully and thoroughly prior to usage. •Magnescale reserves the right to change products and specifications without prior notice.

Magnescale Co., Ltd.

International Sales Department 3-1-4 Edagawa, Koto-ku, Tokyo 135-0051, Japan TEL.+81(0)3-6632-7924
Magnescale Americas Inc. 1 Technology Drive, Suite F217, Irvine, CA 92618, USA TEL.+1(949)727-4017
Magnescale Europe GmbH Antoniusstrasse 14, 73249 Wernau, Germany TEL.+49(0)7153-934-291
Service & Parts 45 Suzukawa, Isehara-shi, Kanagawa 259-1146, Japan TEL.+81(0)463-92-2132

http://www.magnescale.com

MAGNESCALE and SmartSCALE is a trademark or registered trademark of Magnescale Co., Ltd., Japan
The contents of this literature are as of Mar. 2023
SmartABS-EA02C
C.2303.CB.500

Magnescale

SPEED X PRECISION



SmartSCALE

Absolute type

Stronger resistance to harsh environments

Magnescale Co., Ltd.

Stronger resistance to harsh environments

Air purging not necessary


Wide gap and clearance tolerance

Gap between scale and head : 2 times greater than current model.
Clearance tolerance between scale and head : 5 times greater than current model.

Magnetic sensor(TMR)
185 μm \pm 100 μm
Scale recording surface

Separate type simple architecture

Space saving design by bearingless and miniaturization enables encoders to install near works and multiple encoders in one axis.



5nm high-resolution

Achieves best in class 5nm resolution by utilizing the latest interpolation technology with a newly developed algorithm.



Sealed structure with IP67 grade

The magnetic encoder and detection device are fully protected by a 50 μm thin metal cover.
High resistance to coolant/water splashing and to sludge/metal chips provides stable operation under harsh environments.



Principle


Detection Principle
A thin-film MR element with a high-precision, low-distortion pattern arrangement is used as the detecting element. The resistance value of the MR element changes when the magnetic field acting on the element changes due to an alteration in the relative position between the element and the magnetic media. This change in resistance value is read electronically to detect the amount of positional change.



New technology


Development of a new magnetic medium

The output detection signal has improved 30% by changing the composition and consistency of the magnetic medium of the scale, and by improving the production method.




The development of a high sensitivity sensor using a new TMR device

Utilizes a low strain sensor enabling 10 times higher sensitivity compared to the current model by the development of a TMR element based on the Spin-Valve method.



New interpolation calculation method

Achieves 5nm resolution and improves interpolation accuracy by utilizing a new interpolation calculation method.



1/1200 \rightarrow 1/12800